



KALU TRACK

spot for 240V 3-phase track, QPAR111, black, max. 75 W, incl. 3-phase adapter

Adjustable spot KALU TRACK with suitable adapter for the 240V 3-phase track system. Conceived as an extension to the popular KALU series, this track spot takes on the shape of the product family. By the incorporated GU10 lamp holder, the spot is suitable to take LED and halogen ES111 lamps. To meet all lighting requirements, we alternatively offer versions with G53 socket and such with incorporated Philips LED modules for the 1- and 3-phase systems.

TECHNICAL DATA

| | |
|---------------------------|--|
| Item no.: | 152610 |
| Socket | GU10 |
| Lamp | QPAR111 |
| Number of sockets | 1 |
| Lamps included | 0 |
| Primary nominal voltage | 230V ~50Hz mA/V |
| Tilt range | 90 ° |
| Horizontal rotation range | 350 ° |
| Length | 18.0 cm |
| Diameter | 12.0 cm |
| Net weight | 0.32 kg |
| Gross weight | 0.43 kg |
| IP Code | IP 20 |
| Safety class | II |
| Assembly | Surface |
| Assembly details | Ceiling, Track Ceiling, Track Wall, Wall |
| Wattage | 75.0 W |
| Color | black |
| BIG WHITE Page | 358 |

Recommended lamp

| | |
|---------|---|
| 1001242 | LED lamp , GU10 111mm 30° 2700K |
| 1003087 | LED lamp , QPAR111, GU10, 4000K, 1100lm, 30°, dimmable |
| 551882 | LED ES111 , lamp, 6.5W, COB LED, 38°, 2700K, not dimmable |

Notes
